## Preset Configuration for DN-S1200

- ✓ Ensure that both Denon DN-S1200 controllers are powered on and connected via USB to your computer (PC/MAC)
- ✓ On the 1<sup>st</sup> DN-S1200 (or Left Deck), initiate the preset mode by holding the "preset" button down for 2 seconds, then turn the parameter knob to "MIDI CH SET", push down on the parameter knob and select "1" (it should already be set there by default) Push down on the parameter knob again for next step.

(Left Deck)



✓ Turn the parameter knob "UNIT NO SET", push down on the parameter knob and select "1", then press the CUE button to exit and save.

(Left Deck)



✓ On the 2<sup>nd</sup> DN-S1200 (or Right Deck), initiate the preset mode by holding the "preset" button down for 2 seconds, then turn the parameter knob to "MIDI CH SET", push down on the parameter knob and select "2".

Push down on the parameter knob again for next step



(Right Deck)

✓ Turn the parameter knob "UNIT NO SET", push down on the parameter knob and select "2", then press the CUE button to exit and save.



(Right Deck)

\*You have now completed the Preset Configuration.

\*Set each player to "PC Mode"

## 4. Configuration of DN-S1200 with MAC Audio/MIDI Setup

000	A	udio MI	DI Setup			_	_	_	_
	Audio D	evices	MIDI Devic	es					
System Settings Default Input: <b>É</b> Built-	in Microphone	•	Default Out System Out	put: put:	€ Bu ∳ DI	uilt-ir N-S1	n Outp 200	ut	
Properties For: 🖞 DN-S	1200	\$							- (
Clock Source: Default		A V	Configur	re Speal	ers				
Audio Input			Audio Outp Master S Source: Format:	itream Defa	ult 0.0 Hz		¢	-16bit	\$
Input is not s	upported		Ch Volume M O 1 O 2 O			_	Value NaN 	dB -127.3	Mute

- On the MAC, go to Applications > Utilities > Audio MIDI Setup

- At the top Menu bar select Audio > Open Aggregate Device Editor



- Click on the "+" symbol to add a new aggregate device

00	_	-	Audio MIDI	Setup	_		
System Settings – Default Input:	Aggregate Devices In Out						Jutput
Properties For:	+ -						
udio Input —	Clock	Use	Audio Device	In	Out	Resample	¢
	(?)			0		Done	alue dB Mute NaN -127.31
Input i	s not sup	por	red				

- You will now see the option to select the 2 DN-S1200 units.

000	_	-	Audio MI	OI Setup	_	_	
System Settings - Default Input:	Aggrega Aggrega	ite De te De	vices vice	MOLDEN		In Out 0 0	Dutput \$
Properties For:	+ -	Add	and remove aggregat	e devices on	your co	omputer	
Audio Input —	Clock	Use	Audio Device Built-in Microphone Built-in Input Built-in Output DN-S1200 DN-S1200	In 2 2 0 0 0	Out 0 2 2 2	Resample	¢ 2ch-16bit ¢ alue dB Mute NaN -127.31
Input	is not sup	por	ted	2.0	-		

- Select both DN-S1200 units by putting check marks in the "Use" column, then press Done.

00	_	-	Audio MIDI Se	tup	_	_	
System Settings – Default Input:	Aggrega Aggrega + –	te De te De	e Device				
Properties For:	Structu	re:	*				(
Clock Source:	Clock	Use	Audio Device	In	Out	Resample	
Audio Input	O	M	DN-51200	0	2		
auto input	ŏ	V	DN-51200	0	2	A	
	ŏ		Built-in Microphone	2	0	ă	* *
	0		Built-in Input	2	0	0	\$
	0		Built-in Output	0	2		24.2512
Input i	is not sup	por	ted				

- You can now exit out of Audio MIDI Setup.